

# DMX Address Writer LED-DW100

Set starting address for led fixture



## Introduction: >>>

No.	Function	Remark
1	PWR	2 Pin power input cable , power supply for address writer (9~24V)
2	Signal	3/5 Pin XLR signal output cable, connect with led fixture DMX signal input cable
3	Display screen	Display the current address(the corresponding light will light up)
4	+	Display screen address add 1
5	-	Display screen address minus 1
6	Enter	Confirm the display screen's address

## How to use: >>>

- 1, Connect led fixture, address writer, power supply correctly and power on.
- 2, Press "+" until display show the address you want, press "enter"
- 3, Corresponding led will light on when you press "+" or "-".

### Example 1

set 8pixel led bar address 001-024.

- 1, Connect dmx led bar, address writer, power supply correctly and power on.
- 2, Press "+", and when it display "001"
- 3, Press "enter", the 1st pixel will be red
- 4, Press "+", it display "002", the 1st pixel will be green
- 5, Press "+", it display "003", the 1st pixel will be blue
- 6, Disconnect connection. Set address for other lights if necessary.

